

# EST-CU-11LT

## Control Unit (11 control slots)

### Overview

EST-CU-11LT Control Unit (CU) is a matrix mixer of input signals which routes to 4 x 100 V internal audio buses, a 45-channel digital system buses or directly to audio outputs in a unit. EST-CU-11LT is designed to work for small PA & VE systems or as an extension unit in more complex systems. It means that the CU can function independently as the central unit of a small system or be part of a large complex system for which it represents another level of either territorial extension (operation in a remote structure) or functional extension (operation of further fire zones and loudspeaker lines in such a structure).

The modular design of the CU and its flexibility enables optimization of equipment and cost efficiency regardless of size / number of structures, their location and connectivity.

In the event of losing connectivity with a networked master unit, EST-CU-11LT is able to perform fire alarm scenarios independently thanks to the configuration recorded locally. While attached to the main communication ring of the system, EST-CU-11LT can control amplifiers and power supply managers as well as receive alarm and digital signals; and send them to other system devices.

EST-CU-11LT Control Unit distributes audio signals to individual zones and ensures that individual zones function properly. It also controls the condition of loudspeaker lines and amplifiers. If a fault is detected, it sends the signal to the system and automatically switches to a backup amplifier.

The CU is equipped with an EST-cAudio-4/12 card offering 4 symmetrical line audio inputs and 12 symmetrical outputs to lead audio signals out to external devices or amplifiers of the EST ENT VES system.



### Details

- Compliance with EN54-16
- Network-based system allowing configuration, diagnostics and management via Ethernet
- Managing up to 254 devices on the network
- 11 slots available for any configuration of loudspeaker control cards and control input / output cards
- Built-in audio card with 4 inputs and 12 audio outputs
- Up to 12 messages played simultaneously in different zones
- Up to 32 GB SD flash memory designated for playback and recording messages (48 kHz, 16 bit)
- 1x POE port
- Support of up to 12 secured amplifiers
- Built-in 2 control inputs and outputs
- 2x 1 GB ports available for system extension
- Integrated DSP with implemented 3 band parametric EQ on all inputs on control units, 8 band parametric EQ, delay lines, audio limiter and feedback eliminator on each of the audio outputs
- Comprehensive solution based on RS485 functionality enabling seamless integration of the EST ENT VES system with 3rd party systems thanks to implementation of standard and proprietary communication interfaces

# EST-CU-11LT

## Control Unit (11 control slots)

### Technical specifications

#### Eléctrico

Consumo de corriente	Up to 100 W (depends on configuration)
----------------------	--

#### Entrada

Cantidad y tipo	4, Differential
-----------------	-----------------

#### Salida

Cantidad y tipo	12, Balanced
-----------------	--------------

#### Físico

Dimensiones físicas	482 x 85 x 325 mm (W x H x D)
Peso neto	Up to 8.4 kg (depends on configuration)
Tipo de montaje	Bastidor de 19"

#### Medioambiental

Temperatura de funcionamiento	0°C to +60°C
Temperatura de almacenamiento	-20°C to +70°C

#### Estándares y regulaciones

Normativas	EN54-16
------------	---------

#### Electrical

Power supply	48 VDC (operating range 40-57 VDC) connector with screw terminals M2.5, the distance between the partitions of 5.08 mm
--------------	--

#### Physical

Number of control slots	11
Number of function slots	0
Messages	Supported SD card up to 32 GB. The set includes 512 MB SLC SDHC cards which provides more than 20 min of the messages
DSP	Implemented 3 band parametric EQ on all 4 inputs of the control units 8 band parametric EQ, audio limiter, feedback eliminator and delay line on all of the audio outputs
Fiber module - connector type / kind of fiber	Modules type SFP / Connector SC/LC / Multimode or single-mode / E 30 or E 90, OM lub OM2
Communication with PC	PC software: RJ45 connector twisted pair connection TIA / EIA568-B by the Ethernet protocol
Available communication protocols	Modbus, SMS
Finish case material	Steel / The front panel is made of metal plate painted black
Accessories	2 brackets and 4 screws for rack mounting, 9 caps for free slots, 48 VDC power and 100 V buses connectors

#### Input

Connector type	1x RJ45
Input impedance	≥ 10 kΩ
Maximum input voltage	≥ 3 Vrms

#### Output

Connector type	3x RJ45
Frequency response	40 Hz... 20 kHz (at 1 dB) / 400 Hz... 8 kHz (at 0,1 dB)
Harmonic distortion (THD+IMD)	≤ 0,05%
Headroom	10 dB
SNR	≥ 90 dB
Channel separation	≥ 80 dB
Output impedance	600 Ω
Nominal output level	1 Vrms

#### Data communication

1000BASE-X on the fiber

2 SFP ports provide a redundant connection

1000BASE-TX / RJ45  
CAT5E cables - 2 ports  
including 1 port with POE

100BASE-TX / RJ45 CAT5  
cables - LAN/WAN for PC  
connection

#### Environmental

Operating humidity	15% to 80% non-condensing
Storage humidity	15% to 80% non-condensing



Como empresa innovadora, Carrier Fire & Security se reserva el derecho de modificar las especificaciones de los productos sin previo aviso. Para conocer las últimas especificaciones de los productos, visite la Web de [es.firesecurityproducts.com](http://es.firesecurityproducts.com) o póngase en contacto con su comercial.

Last updated on 7 December 2021 - 16:05